



**DAT01A**  
1A Mains Bell Transformer  
Surface Mounted  
4/8/12V AC



**DAT02A**  
1A Mains Bell Transformer  
DIN Rail Mounted  
4/8/12V AC



**DAT03A**  
2A Mains Transformer  
DIN Rail Mounted or Surface  
Mounted  
4/8/12V AC

**Note: DAT01A & DAT02A**  
The DAT01A & DAT02A are suitable for use  
with Ring & Nest systems.

The 'Off Load' for both Ring & Nest  
system needs to be above 16V.

Both transformers 'Off Load' are above this.  
Only when using the 12V tappings.

### FEATURES

- ▶ DAT02A & DAT03A are Din Rail Mounted
- ▶ Conforms to BS EN 61558-2-8

### TECHNICAL INFO

Product	DAT01A	DAT02A	DAT03A
<b>Description</b>	1A Mains Bell Transformer Surface Mounted 4/8/12V AC	1A Mains Bell Transformer Din Rail Mounted 8/12V AC	2A Mains Bell Transformer Din Rail Mounted or Surface Mounted 4/8/12V AC
<b>Product Finish</b>	Grey RAL7035		
<b>Voltage - Full Load</b>	230V ~ primary 4/8/12V ~ 1A Secondary output	230V ~ primary 8/12V ~ 1A Secondary output	230V ~ primary 4/8/12V ~ 2A Secondary Output
<b>IP Rating</b>	IP40	IP20	
<b>Barcode</b>	5012739 628535	5012739 626555	5012739 627026
<b>Product Weight</b>	293g	352g	831g
<b>Dimensions</b>	H80 x W56 x D43mm	H90 x W36 x D63mm	H90 x W54 x D63mm
<b>Guarantee</b>	1 Year		
<b>Conforms To</b>	BS EN 61558-2-8		