



RCDA

### FEATURES

- ▶ Suitable for use with all makes of electrical & gardening appliances
- ▶ Electrically latched - will need to be reset after a power loss
- ▶ Cuts the power for added protection against electrocution
- ▶ All products have a separate 'Test' & 'Reset' button
- ▶ Large, clear indicator window, flags Red (RCDA & L) or Orange (RCDP) when 'On'



RCDP



RC DL

### TECHNICAL INFO

Product	RCDA	RCDP	RC DL
<b>Description</b>	RCD Adaptor	RCD Plug	RCD In-line
<b>Barcode</b>	5012739 627156	5012739 627163	5012739 634451
<b>Product Finish</b>	White		
<b>Product Weight</b>	165.5g	140g	213g
<b>Product Dimensions</b>	H128 x W50 x D50.9mm	H123 x W49.5 x 54mm (not including cable gland 24mm)	H210 x W60mm
<b>Voltage</b>	230VAC ~ 50Hz	230/250V AC ~ 50/60Hz	
<b>Max Operating Temperature</b>	13A (13A Inductive)		13A (4A Inductive)
<b>IP Rating</b>	IP40	IP54	IP55
<b>No of Poles</b>	2		
<b>Rated Trip Current</b>	30mA		
<b>Typical Trip Speed</b>	Less than 40mS (typical)		
<b>RCD Contact Break</b>	Double Pole		
<b>Latching</b>	Electrical - Needs to be reset after Power Loss (Active)		
<b>Responsive to</b>	Pulsating DC earth faults - Type A RCD		
<b>Main Housing Material</b>	Polycarbonate		
<b>Guarantee</b>	1 Year		
<b>Conforms to</b>	BS 7071 & BS 1363		BS 7071 & BS 61543